

## **PRODUCT CARD**



PRODUCT CODE: OR-CR-264 EAN CODE: 5900378654780

## Motion sensor 360°, IP65

This motion sensor is used to automatically control lighting or other electric appliances. The device is equipped with potentiometers to adjust lighting time and light intensity. It is compatible with LED diodes.



Degree of protection (IP):

65



Adjustable daylight sensor (LUX):



Detection angle:

360°



Max. load: 2000W



Adjustable time setting (TIME):



Type of sensor:



Nominal voltage:

230V~, 50Hz



**Detection range:** 

m



## General information

Degree of protection (IP):	65
Max. load of the LED light source:	500 W
Max. load:	2000 W
Colour:	white
Nominal voltage:	230V~, 50Hz
Relay output:	no
Presence detector:	no
Adjustable daylight sensor (LUX):	yes
Dimensions of the sensor - width (mm):	mm
Installation:	surface mounting
Dimensions of the sensor - height (mm):	mm
Daylight sensor adjustment range (LUX):	<3—2000lux
Dimensions of the sensor - depth (mm):	27 mm
Adjustment of motion detection range (SENS):	no
Adjustable time setting (TIME):	yes
Lighting time adjustment range (TIME):	min.: 10 sek. ± 3 sek., max.: 15min.±2min
Detection range:	m
Detection angle:	360°
Type of sensor:	
Other features:	